

DIAGNOSTIC TROUBLE CODE CHART

If a DTC is displayed during the DTC check, check the circuit listed for that code in the table below and proceed to the page given.

DTC No. (See Page)	Detection Item	Trouble Area	MIL *	Memory
P0500 (DI-144)	Vehicle Speed Sensor Malfunction (No.1 Vehicle Speed Sensor)	<ul style="list-style-type: none"> • Open or short in No.1 vehicle speed sensor circuit • No.1 vehicle speed sensor • Combination meter • ECM 	●	○
P0750 (DI-145)	Shift Solenoid A Malfunction (Shift Solenoid Valve No.1)	<ul style="list-style-type: none"> • Shift solenoid valve No.1 is stuck open or closed • Valve body is blocked up or stuck 	●	○
P0753 (DI-146)	Shift Solenoid A Electrical Malfunction (Shift Solenoid Valve No.1)	<ul style="list-style-type: none"> • Open or short in shift solenoid valve No.1 circuit • Shift solenoid valve No.1 • ECM 	●	○
P0755 (DI-145)	Shift Solenoid B Malfunction (Shift Solenoid Valve No.2)	<ul style="list-style-type: none"> • Shift solenoid valve No.2 is stuck open or closed • Valve body is blocked up or stuck 	●	○
P0758 (DI-146)	Shift Solenoid B Electrical Malfunction (Shift Solenoid Valve No.2)	<ul style="list-style-type: none"> • Open or short in shift solenoid valve No.2 circuit • Shift solenoid valve No.2 • ECM 	●	○
P0770 (DI-150)	Shift Solenoid E Malfunction (Shift Solenoid Valve SL)	<ul style="list-style-type: none"> • Shift solenoid valve SL is stuck open or closed • Valve body is blocked up or stuck • Lock-up clutch 	●	○
P0773 (DI-152)	Shift Solenoid E Electrical Malfunction (Shift Solenoid Valve SL)	<ul style="list-style-type: none"> • Open or short in shift solenoid valve SL circuit • Shift solenoid valve SL • ECM 	●	○
P1520 (DI-155)	Stop Light Switch Signal Malfunction	<ul style="list-style-type: none"> • Open or short in shift solenoid valve SL circuit. • Stop light switch • ECM 	●	○
P1700 (DI-156)	Speed Sensor No.2 Circuit Malfunction (No.2 Vehicle Speed Sensor)	<ul style="list-style-type: none"> • Open or short in No.2 vehicle speed sensor circuit • No.2 vehicle speed sensor • ECM 	●	○
P1780 (DI-160)	Park/Neutral Position Switch Malfunction	<ul style="list-style-type: none"> • Short in park/neutral position switch circuit • Park/neutral position switch • ECM 	●	○

* : ●...MIL light up